

tbpt Standard SMS+ HTTP protocol

command	Example	Response	Description
1	001#0000	MSP340_2012062501_FLEET_209	Read software version
111	111#0000	#TK_GPS MSP340A http://maps.google.com/?q=25.070310N,121.592933 IMEI=357852039494938 S=15.8 C=254 SAT=12 V=4.42 CSQ=99 M=Inquiry SN=96381	Inquiry when GPS fixed
		#TK_LBS MSP340A http://www.map110.com/?x=030.94&y=119.14 IMEI=357852039494938 V=4.42 CSQ=99 GPS=ON M=Inquiry SN=96381	Inquiry when GPS no fixed or OFF
200	200#0000	GPS OFF !	Turn off GPS
	201#0000	GPS ON !	Turn on GPS
410	410#0000	IMEI=355543020119954	Read IMEI
512	512#0000#Report mode#Interval time	Interval time = HHMMSS For 5 min =000500 , 30 sec =000030 , 1 min =000100	Only for GPRS , you must setup APN
	512#0000#1#000500	SETUP OK: Report mode=5 min	Interval time = HHMMSS For Example 5 min =000500 , 30 sec =000030 , 1 min =000100
510	510#0000#internet#http.minisentry.com#80#/gps.asp	SETUP OK: APN=internet, IP=http.minisentry.com:80/gps.asp	development by self (HTTP protocol & customer server)
	510#0000#internet	SETUP OK: APN=internet, IP=http.minisentry.com:80/gps.asp	User Traccker Technology Service
	510#0000	APN=internet, IP=http.minisentry.com:80/gps.asp	Read APN/IP/Port
	510#0000#0	SETUP OK: APN=None, IP=http.minisentry.com:80/gps.asp	Delete APN
513	Please pay attention , if you change the Sleep mode time , the battery life will		
	513#0000#1#000300	SETUP OK: Sleep mode=GSM and GPS OFF, Sleep time=000300	Setup Sleep mode 、 Sleep time
	513#0000	Sleep mode=GSM and GPS OFF, Sleep time=000500	Read Sleep mode 、 Sleep time
	513#0000#0	SETUP OK: Sleep mode=Sleep mode disable, Sleep time=000300	Disable Sleep mode
	513#0000#9#000100	SETUP OK: Sleep mode=GSM and GPS OFF, Sleep time=000100	Setup Sleep time < 3 minutes
514	514#0000#1111	SETUP OK: SMS password=1111	Setup SMS password
515	515#0000#0981#0958#0975	SETUP OK: SOS phone number=0981, 0958, 0975	Setup phone number
	515#0000	phone number=0981, 0958, 0975	Read phone number
800	800#0000#ftp.tracker.com.tw#ftpuser#12345678#home#GPSLED.bin	Tracker software update now.	FOTA